


GENERAL INFORMATION



LINIAR COMPONENTS





LSW041 SCULPT. BEAD LCW041 CHAMF. BEAD SCALE: 1:1

STEELS **LSR091** St St Track

LSR092 LSR092P (PUNCHED) Sash Reinforcing

ANCILLARIES LBF043 LBF192

Tenon/Finger Pull

LMO191 LBF193 Meeting Stile End Cap Eurogroove Insert

SCALE: 1:2

SCALE: 1:1

2 3 **LBF194 LBF196 LBF197** Interlock Seal Brush Pile Q-Lon


Channel Capping

SCALE: 1:1


LINIAR COMPONENTS








Double Roller Top/Btm Note: Top Roller Sprung Loaded



LBF071Butt Hinge
Optional: Coupled with 'C' Handle




LBF060

LBF072 'C' handle

Single Roller Top/Btm Note: Top Roller Sprung Loaded

HARDWARE HANDLES






LBF041

Door Magnets

Note: North & South Poles



LBF042Escutcheon/Lock Plt.


SCHEMES AND DEDUCTIONS

All schemes can be made in opposite hand. Equal sash sizes unless otherwise stated. Some schemes require larger sash sizes noted at areas 'x' using specified cutting deductions SW(x) & G(x).

W - Frame Width SW - Sash Width G - Glass Size

Scheme 220

2 Folding sashes, 0 Main opening sash




SW = ((W-104)/2)-31G = ((W-372)/2)-31

SW(x) = ((W-104)/2)+31G(x) = ((W-372)/2)+31

Scheme 321

2 Folding sashes, 1 Main opening sash




SW = ((W-136)/3)-20.66G = ((W-538)/3)-20.66

SW(x) = ((W-136)/3)+41.34G(x) = ((W-538)/3)+41.34


Scheme 330

3 Folding sashes, 0 Main opening sash



SW = (W-112/3)G = (W-514/3)


Scheme 431
3 Folding sashes, 1 Main opening sash



SW = (W-144/4)G = (W-680/4)

Scheme 440

4 Folding sashes, 0 Main opening sash




SW = ((W-120)/4)-15.5G = ((W-656)/4)-15.5

SW(x) = ((W-120)/4)+46.5G(x) = ((W-656)/4)+46.5

Scheme 422

2+2 Folding sashes, 0 Main opening sash




SW = ((W-120)/4)-31G = ((W-656)/4)-31

SW(x) = ((W-120)/4)+31G(x) = ((W-656)/4)+31

Scheme 541

4 Folding sashes, 1 Main opening sash




SW = ((W-152)/5)-12.4G = ((W-822)/5)-12.4

SW(x) = ((W-152)/5)+49.6G(x) = ((W-822)/5)+49.6

Scheme 550


5 Folding sashes, 0 Main opening sash



SW = (W-128/5)G = (W-798/5)

Scheme 532

3+2 Folding sashes, 0 Main opening sash




SW = ((W-152)/5)-12.4G = ((W-822)/5)-12.4

SW(x) = ((W-152)/5)+49.6G(x) = ((W-822)/5)+49.6

Scheme 651

5 Folding sashes, 1 Main opening sash



SW = (W-160/6)G = (W-964/6)

whiteline

All schemes can be made in opposite hand.

Equal sash sizes unless otherwise stated.


Some schemes require larger sash sizes noted at areas 'x'

using specified cutting deductions SW(x) & G(x).

W - Frame Width SW - Sash Width G - Glass Size

Scheme 660

6 Folding sashes, 0 Main opening sash




SW = ((W-136)/6)-10.33G = ((W-940)/6)-10.33

SW(x) = ((W-136)/6)+51.67G(x) = ((W-940)/6)+51.67

Scheme 633


3+3 Folding sashes, 0 Main opening sash



SW = (W-160/6)G = (W-964/6)

Scheme 761

6 Folding sashes, 1 Main opening sash




SW = ((W-168)/7)-8.86G = ((W-1106)/7)-8.86

SW(x) = ((W-168)/7)+53.14G(x) = ((W-1106)/7)+53.14

Scheme 770


7 Folding sashes, 0 Main opening sash



SW = (W-144/7)G = (W-1082/7)

Scheme 743

4+3 Folding sashes, 0 Main opening sash




SW = ((W-168)/7)-8.86G = ((W-1106)/7)-8.86

SW(x) = ((W-168)/7)+53.14G(x) = ((W-1106)/7)+53.14

Scheme 752


5+2 Folding sashes, 0 Main opening sash





SW = ((W-168)/7)-8.86G = ((W-1106)/7)-8.86

SW(x) = ((W-168)/7)+53.14G(x) = ((W-1106)/7)+53.14


TYPICAL ASSEMBLIES (int. folding)







TYPICAL ASSEMBLIES (int. folding)




GLAZING



All glazing must fall in line with the requirements of BS6262 and any recommendations of the glass manufacturers.


The correct use of glazing packers is critical to allow the bi-fold doors to function correctly. The diagram below shows both a left and right opening door and the position of the glazing packers. The dashed lines, as shown in Section 3, indicate the position of the load bearing packers for all of the typical assemblies.

It is essential that the glass stays in position and we therefore recommend that where necessary the packers are siliconed into position. Ensure that all packers do not obstruct any drainage holes.



HINGE ADJUSTMENT





BUTT HINGE ADJUSTMENT

Add/Remove hinge packers to adjust each hinge independently.


2 Packers = Nominal 8mm Gap Total hinge adjustment: ±2mm


LBF050, DOUBLE ROLLER

Adjust both top & bottom rollers to minimum point for sash assembly in frame.

Once assembled in frame adjust back to nominal to suit nominal 8mm door gap.

Adjust top roller to suit desired compression. Adjustment: ±10mm, 6mm Allen Key Required.





LBF060, SINGLE ROLLER

Remove top single roller for door assembly. Fix in position once door is assembled.

Adjust bottom roller to suit 8mm nominal door gap.

Adjust top roller to suit desired compression. Adjustment: +5mm, -2mm, 5mm Allen Key Required.



SURVEY AND INSTALLATION

Due to copyright laws, Liniar are unable to reproduce extracts from the following publication:

BS 8213-4:2007

Windows, doors and rooflights. Code of practice for the survey and installation of windows and external doorsets.


However, a copy can be ordered from the following website:

www.bsi-global.com

Please ensure all doors are issued on manufacture, with the most current Bi-Fold installation and operation guide.

Ensure outer frame is packed out to be parallel, level & true.

Maximum deviation ±2mm





MAINTENANCE

FRAMES & TRACK (FREQUENCY AS REQ.)

To ensure frames & track are free of dirt, clean regularly with soap and water. Drainage holes are to be checked, and any blockages removed.

WOOD GRAIN FRAMES

Cleaning as above.

Minor scratches can be repaired using a wood grain marker pen.

HINGES, HANDLES & LOCKING MECHANISMS (FREQUENCY - ANNUALLY)

Wipe clean with cotton cloth & lubricate pivot points with light machine oil.

Check for obstructions & signs of wear.

Check all fixing screws are secure.